
1373 1377

取扱説明書使用说明书

取扱説明書 INSTRUCTION MANUAL



注意: このたびは、当社の製品をお買い上げいただきまして、ありがとうございました。 安全に使用していただくために使用前に、必ずこの取扱説明書をお読みください。 また、いつでもすぐに読めるように、この取扱説明書を保管してください。

NOTE: Read safety instructions carefully and understand them before using. Retain this instruction Manual for future reference.

注意: 为了安全地使用,请您在使用之前一定阅读本使用说明书。 另外,请您注意保管本使用说明书,以便随时查阅。

ENGLISH

Putting sewing systems into operation is prohibited until it has been ascertained that the sewing systems in which these sewing machines will be built into, have conformed with the safety regulations in your country.

Technical service for those sewing systems is also prohibited.

- 1. Observe the basic safety measures, including, but not limited to the following ones, whenever you use the machine:
- 2. Read all the instructions, including, but not limited to this Instruction Manual before you use the machine. In addition, keep this Instruction Manual so that you may read it at anytime when necessary.
- 3. Use the machine after it has been ascertained that it conforms with safety rules/standards valid in your country.
- All safety devices must be in position when the machine is ready for work or in operation.
 The operation without the specified safety devices is not allowed.
- 5. This machine shall be operated by appropriately-trained operators.
- 6. For your personal protection, we recommend that you wear safety glasses.
- 7. For the following, turn off the power switch or disconnect the power plug of the machine from the receptacle.
 - 7-1 For threading needle(s), looper, spreader etc. and replacing bobbin.
 - 7-2 For replacing part(s) of needle, presser foot, throat plate, looper, spreader, feed dog, needle guard, folder, cloth guide etc.
 - 7-3 For repair work.
 - 7-4 When leaving the working place or when the working place is unattended.
 - 7-5 When using clutch motors without applying brake, it has to be waited until the motor stopped totally.
- If you should allow oil, grease, etc. used with the machine and devices to come in contact with your eyes or skin or swallow any of such liquid by mistake, immediately wash the contacted areas and consult a medical doctor.
- 9. Tampering with the live parts and devices, regardless of whether the machine is powered, is prohibited.
- 10. Repair, remodeling and adjustment works must only be done by appropriately trained technicians or specially skilled personnel. Only spare parts designated by JUKI can be used for repairs.
- 11. General maintenance and inspection works have to be done by appropriately trained personnel.
- Repair and maintenance works of electrical components shall be conducted by qualified electric technicians or under the audit and guidance of specially skilled personnel.

Whenever you find a failure of any of electrical components, immediately stop the machine.


- 13. Before making repair and maintenance works on the machine equipped with pneumatic parts such as an air cylinder, the air compressor has to be detached from the machine and the compressed air supply has to be cut off. Existing residual air pressure after disconnecting the air compressor from the machine has to be expelled. Exceptions to this are only adjustments and performance checks done by appropriately trained technicians or specially skilled personnel.
- 14. Periodically clean the machine throughout the period of use.
- 15. Grounding the machine is always necessary for the normal operation of the machine. The machine has to be operated in an environment that is free from strong noise sources such as high-frequency welder.
- 16. An appropriate power plug has to be attached to the machine by electric technicians. Power plug has to be connected to a grounded receptacle.
- 17. The machine is only allowed to be used for the purpose intended. Other used are not allowed.
- 18. Remodel or modify the machine in accordance with the safety rules/standards while taking all the effective safety measures. JUKI assumes no responsibility for damage caused by remodeling or modification of the machine.
- 19. Warning hints are marked with the two shown symbols.



Danger of injury to operator or service staff



Items requiring special attention



FOR SAFE OPERATION



- To avoid personal injury, never put your fingers under the needle when you turn ON the power switch or operate the sewing machine.
- 2. To avoid personal injury, turn OFF the power switch when you tilt the machine head.
- 3. To prevent possible personal injury caused by being caught in the machine, keep your fingers, head and clothes away from the handwheel and the thread take-up while the sewing machine is in operation. In addition, place nothing around it.
- 4. Never operate the machine with the safety devices such as needle bar cover, finger guard, eye guard cover, etc. removed.
- 5. To avoid personal injury, be careful not to allow your fingers in the machine when tilting the machine head.



- 1. For the safety, never operate the sewing machine with the ground wire for the power supply removed.
- 2. Be sure to turn OFF the power switch in prior when connecting/disconnecting the power plug.
- 3. When thunders occurs, stop the work for the safety and disconnect the power plug.
- 4. When the sewing machine is suddenly moved from a cold place to a warm place, there is a case where dew condensation may occur. Turn ON the power after there is no worry of the drop of water.
- To prevent fires, periodically draw out the power plug from the plug socket and clean the root of the pins and the space between pins.

CAUTION BEFORE OPERATION



WARNING:

To avoid malfunction and damage of the machine, confirm the following.

- · Use the oil adaptable to the machine specifications.
- · Clean the sewing machine thoroughly before using it for the first time.
- · Remove all dust collected on the sewing machine during the transportation.
- · Confirm that the voltage and phase are correct.
- · Confirm that the power plug is properly connected.
- Never use the sewing machine in the state where the voltage type is different from the designated one.
- The direction of rotation of the sewing machine is clockwise as observed from the handwheel side. Be careful not to rotate it in reverse direction.
- Before applying power, release the stop-motion mechanism and turn by hand the needle driving pulley in order to ensure that the machine is in order.
- To install the machine, the frame support bar has to be firstly inserted into the table.
- When operating the sewing machine, turn ON the power switch after properly setting the head on the table.
- · Operate the handwheel after the sewing machine has totally stopped.

CONTENTS


1. SPECIFICATIONS	
2. PREPARATION OF THE SEWING MACHINE	1
2-1. Installation	2
2-3. Attaching the needle2-4. Attaching the needle bar cover	3
o c Threading the machine	
OF THE CAMING MACHINE	. 4
3-1. Thread tension adjustment	4
3-2. Adjustment of the thread pull-off lever	5
3-3. Adjusting the tension lever	5
3-5. Adjusting the thread tension guide on the face plate	6
3-7. Position of the needle guide	6
3-8. Height of the button clamp	6
the state of the s	
4 11 1	
3-15. Automatic thread trimmer	9
3-16. Clearance between the button clamp litting level and the daysoning and 3-17. How to set the L-shaped lifting rod	10
(4) Changeover of with/without knot-tying	
TARREST ANCE SUBCLASS MODELS AND ATTACHMENTS	11
	11
4-3. Attachments	13
(5) Attachment for metal buttons (2036)	18
4-4. Motor pulley and bettimental MEASURES	10

1. SPECIFICATIONS

	MB-1373	MB-1377	
Sewing speed	Normal 1,300 rpm	(Max. 1,500 rpm)	
Number of stitches	8, 16 and 3	2 stitches	
Feed amount	Lateral feed 2.5 to 6.5mm	Lateral feed 2.5 to 6.5mm	
	Longitudinal feed 0, 2.5 to 6.5mm	Longitudinal feed 0, 2.5 to 4.5mm	
Button size	10 to 2	8 mm	
Needle used	TQx1 #16 (#14 to #20)	TQx7 #16 (#14 to #20)	
Lubricating oil	JUKI New Det	frix Oil No. 1	
Noise	Workplace-related noise at sewing speed n = 1,500 min–1 : Lpa ≤ 84 dB(A) Noise measurement according to DIN 45635-48-B-1.		

2. PREPARATION OF THE SEWING MACHINE


2-1. Installation





Put rubber cushion ① on the table, place the machine head on the rubber cushion and fix it to the table using screws ②, plain washers ③ and nuts ④. Attach "S" chain hook ⑥ and chain ⑦ to stop motion trip lever ⑤.




To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.










- 1) Open the side cover, and apply JUKI New Defrix Oil No. 1 to the portions shown by the red marks (1) to (2) (1): MB-1377 only). (Apply approximately 1 cc of oil to the respective lubricating places one to two times a week.)
- Loosen connecting screw (3), tilt the machine head backward and apply grease (JUKI designated grease) to crossed helical gear 🚯 and worm gear 🚯.
- 3) Check, approximately once a week, that oil amount is sufficient to reach the top of the oil felt placed inside the bed mounting base. If the amount of oil is insufficient, add an adequate amount of oil. At this time, also apply oil to crank rod (1).




[Caution at the time of lubricating]

- Take care not to allow speed slowing friction wheel (1) and friction plate (2) to be clogged with oil to prevent them from the deterioration of retardation performance. In addition, when the components are clogged with oil, wipe the oil from them.
- 2. Take care not to allow the machine belt to be clogged with oil to prevent it from the deterioration.

2-3. Attaching the needle



To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.




★ Use a standard needle of TQx1 #16. Loosen setscrew and hold needle with the long groove facing toward you. Then fully insert it into the hole in the needle bar, and tighten setscrew ().




WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



- 1) Loosen screw 2 and remove thread guide 3.
- 2) Place needle bar guard 1 under thread guide
 - 3 and attach thread guide 3 so that lever 4 comes to the center of it at the start of the machine.
- 3) Fix the cover with screw 2.

2-5. Attaching the button tray assembly




Insert the posts of button tray ① in hole on the right of the machine sub-base and tighten each setscrew ②. If it is difficult for the operator to pick up the buttons on the right side, change it to hole ③ on the left side.

2-6. Threading the machine



WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.




Thread the machine head in the order of ① to ② as shown in the illustration given above. Then, pass the thread through the needle eye from the front for approximately 60 to 70 mm as you depress nipper releasing knurled thumb nut ②.

* Standard needle is TQ X 1 #16.

3. ADJUSTMENT OF THE SAWING MACHINE

3-1. Thread tension adjustment




Tension post No. 1 is used to adjust the thread tension to sew on the button and a relatively low tension will be enough. Tension post No. 2 is used to adjust the thread tension applied to the root of the button sewing stitches. This tension must be determined according to the type of thread, fabric and thickness of the button and must be higher than that of tension post No. 1 in. Turn the tension nuts clockwise to increase or counterclockwise to reduce the thread tension.

3-2. Adjustment of the thread pull-off lever



WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.




To adjust the thread pull-off lever ①, insert a screwdriver through an opening in the machine arm side cover (left), loosen screw ② and adjust the position of nipper bar block (rear) ③ to the left or the right. If the end of thread is drawn from arrow hole A in the button after sewing, change the position of nipper bar block (rear) ⑤ to the left. Move the lever to the right when the thread end comes out from arrow hole B.

3-3. Adjusting the tension lever




WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



- 1) When the machine is in the stop-motion state, loosen screw 1.
- 2) Tighten setscrew 1 so that there is a clearance of 8 to 10 mm as a standard between the end of thread tension guide 3 and end of lever 4.




3-4. Adjusting the nipper




WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



- Provide a 0.4 to 0.6 mm clearance between nipper block 2 and nipper
 to prevent the nipper from holding the thread while the machine is in operation.
- Loosen screw 3 and move nipper bar block 4 to the right or the left.

3-5. Adjusting the thread tension guide on the face plate




If the formation of seams at the start of sewing is failed and the seams are formed on the way even when the thread pull-off lever is adjusted, turn thumb nut (double nut) to decrease the thread tension.

3-6. Needle-to-looper relation



WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



* Adjust the needle-to-looper relation as follows:

1) Depress the pedal fully forward, turn the needle driving pulley in the normal sewing direction by hand to bring down the needle bar to the lowest position of its stroke and loosen screw 1.

(Adjusting the needle bar height)

- 2) Adjust the height of the needle bar using the top two lines engraved on the needle bar 2 for the TQx1 needle and using the bottom two lines for the TQx7 needle. Align the upper line 3 with the bottom end face of needle bar bushing (lower)
 - 3 and tighten screw 1. At this time, tighten the screw so that groove 6 of the needle faces the front.

(Looper position)


- 3) Loosen screws 4 and turn by hand the needle driving pulley until lower line 3 of two lines aligns with the bottom end face of needle bar bushing (lower) 3.
- 4) By keeping the machine in this state, align looper blade5 with the center of the needle and tighten screws 4.
- Loosen screws 6 and provide a 0.01 to 0.1 mm clearance between the looper and the needle. Tighten screws 6.

3-7. Position of the needle guide



WARNING :

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.




Loosen screw 2 and provide a 0.05 to 0.1 mm clearance between the needle guide 1 and the needle by moving the needle guide 1 to the left or the right when the needle is in the lowest position.

3-8. Height of the button clamp



WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.




- 1) The standard clearance between the rear side of the bottom face of button clamp jaw lever and the top surface of feed plate is 8 mm at the position where the machine has stopped after sewing.
- To adjust the height of the button clamp unit, loosen screw 3 in the button clamp lifting hook and move button clamp lifting hook 4 up or down.

3-9. Work pressing force



WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



The standard work pressing force is by providing a 28.5 to 29.5 mm between the top end of nut 1 and the bottom end of pressure adjusting bar 2.


Turn nut 1 to adjust it.

3-10. Adjustment of the button clamp stop lever




WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



When clamp screw 1 is loosened in the state of stop-motion, button clamp jaw levers 3 opens/closes with button clamp stop lever 2. Set a button to the correct position and fix button clamp stop lever 2 at the position where taking in and out of the button is easily performed with clamp screw 1.

3-11. Timing of thread tension release



Turn the needle driving pulley as you draw the thread in the direction of arrow mark (A) and you will find a point at which the tension discs on the tension post No. 2 release the thread. At this moment, the standard distance from the top end of the needle bar bushing (upper) to the top end of the needle bar is 44 to 47 mm (in case of the needle of TQ X 7, 54 to 57 mm).

Perform the following adjustments especially when the undermentioned troubles occur frequently.

Loosen nut (1), insert the blade of a screwdriver to the top slot of the tension post No. 2 and turn it in the direction of arrow mark **B** to lower the height of the thread floating bar and in the opposite direction to raise the height.


Phenomenon	Height of thread floating bar
1. When the stitch made on the wrong side of the	Make the needle bar slightly higher.
workpiece is too loose; 2.When the thread is broken at the time of stop-motion;	Make the needle bar slightly lower.
3. When the thread is broken frequently;	Make the needle bar slightly lower.

3-12. Setting for 2- or 4-hole buttons



WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.





Perform the adjustment after confirming that the sewing machine is located at the position of the stop-motion (refer to "3-14. Adjusting the position of the stop-motion", p.8.).

Measure the distance between two holes in a button and set equally crosswise and lengthwise feed regulators for 4-hole buttons.

[in case of MB-1373]

★ Lengthwise feed

Push down lengthwise feed adjusting lever @ and set it to "0" for 2-hole buttons or a corresponding amount for 4-hole buttons.

★ Crosswise feed

Loosen nut @ and set section (A) of pointer (3) to a corresponding amount. Then tighten nut 2.

[In case of MB-1377]

★ Lengthwise feed

Push down lengthwise feed adjusting lever 1 and set it to "0" for -2-hole buttons or a corresponding amount for 4-hole buttons by the respective procedures below according to the sewing methods.

X stitch: Set the lengthwise feed adjusting lever to the position corresponding to the amount for the button within the range of A. U-sharp stitch: Set the lengthwise feed adjusting lever to the position cor-

responding to the amount for button within the range of B.



When setting the lengthwise feed adjusting lever to the position of) (outside of range of setting the lever), not only the sewing cannot | be performed but also trouble will be caused. Do not set the feed | adjusting lever at the position of C.

★ Crosswise feed

Loosen nut 2 and set section A of pointer 3 to a corresponding amount. Then tighten nut 2.



before operating the machine, ensure that the needle enters the center of each hole in the button.

3-13. Setting a number of stitches




WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.


To change the number of stitches, open the left-hand side cover and change the number of stitches using stitch number adjusting screw 1 and stitch number adjusting lever 4 (optional).

★ How to adjust 8 stitches




To make 8 stitches, loosen stitch number adjusting screw
and fix it to the position as shown in the illustration.

* How to adjust 16 stitches




When stitch number adjusting screw 1 being set for "8 stitches" has arrived at the left end, loosen stitch number adjusting screw 1 and fix it to the position as shown in the illustration.

★ How to adjust 32 stitches



In the state of 16 stitches, stitch number adjusting gear roller 2 which is attached to the large gear 5 comes to the lower side, assemble stitch number adjusting lever 4 (supplied as accessories) using hinge screw 3 (supplied as accessories).

3-14. Adjusting the position of the stop-motion



Adjust so that claw ① of the stop-motion cam comes in contact with stop-motion hook ② when the sewing machine completes the sewing and stops.



When replacing the motor pulley and changing the sewing speed from 1,300 rpm to 1,500 rpm, and vice versa, be sure to readjust the position of the stop-motion.

[Adjusting procedure]

- When the stop-motion hook comes in contact with the stop-motion cam and rebounds, (When there is a clearance between claw 1) and stop-motion hook 2) loosen two stop-motion position adjusting screws 3, turn stop-motion adjusting cam 4 in the direction of A, and fix stop-motion position adjusting screws 3.
- When the stop-motion hook stops before it comes in contact with the stop-motion cam claw
 Loosen two stop-motion position adjusting screws 3, turn stop-motion adjusting cam 4 in the direction of B, and fix stop-motion position adjusting screws 3.


3-15. Automatic thread trimmer

(1) Adjusting the position of the moving knife




WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.




When the presser has completely lifted at the stop-motion position (refer to "3-14. Adjusting the position of the stop-motion", p.8), it is the standard that the clearance between thread trimming connecting plate (front) 1 and the end face of the slit of throat plate 2 is 10 to 11 mm. To adjust the aforementioned clearance, tilt the machine head, remove the oil shield, loosen two nuts 3 and move connecting screw 4 back or forth. When you tighten nuts 3, ensure that joint 5 stays in the horizontal position.

3-16. Clearance between the button clamp lifting lever and the adjusting screw



Provide a 0.5 mm clearance between the end face of button clamp lifting lever
and adjusting screw
at the stop-motion position (refer to "3-14 Adjusting the position of the stop-motion", p.8) and tighten with adjusting screw nut
3.

3-17. How to set the L-shaped lifting rod




Put moving knife push-back spring ②, stop-motion rubber cushion washer ③, stop-motion rubber cushion ④ and stop-motion rubber cushion washer ⑤, in this order, to L-shaped lifting rod ①. Make the jaw of the machine arm come into close contact with the end face of the stop-motion rubber cushion washer at the stop-motion position (refer to "3-14 Adjusting the position of the stop-motion", p.8) and set the L-shaped lifting rod without a play. Then tighten it with screw ⑥.

3-18. Knot-tying mechanisms

WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.


(1) Adjusting the knot-tying connecting plate



Loosen screws
and adjust so that a clearance of 1 to 1.5 mm is provided between the needle 2 and the knot tying plate 3 when the roller of the knottying arm gets on the outmost periphery of the knottying notch.


After the adjustment, ascertain that the needle does not come in contact with the knot-tying

(2) Adjusting the knot-tying arm stopper



When starting the sewing machine and the roller of knot-tying arm does not come into contact with the knot-tying notch, loosen screws
and adjust with stopper 4 so that outside periphery 1 of the needle hole almost aligns with top end ② of the knot-tying plate.

(3) Adjusting the knot-tying notch




Loosen screws
and adjust so that the roller of the knot-tying arm comes in contact with the knot-tying notch when the needle bar goes up at the fourteenth stitch as high as 30 to 35 mm (40 to 45 mm when a TQ x 7 needle is used) above the needle bar upper bushing.



If two knot-tying notches are to be installed (without crossover stitch), make the aforementioned adjustment at the 6th and 14th stitches.

(4) Changeover of with/without knot-tying




To make "with knot-tying", pull knot-tying changeover knob • toward the front and place it to the position in the figure.

To make "without knot-tying", pull knot-tying changeover knob toward the front and place it to the position in the figure.

4. MAINTENANCE, SUBCLASS MODELS AND ATTACHMENTS

4-1. How to connect the metal fittings of the belt



Tighten connecting screws of the belt so that the screws protrude approximately 1.5 to 2 mm from the reverse side as the standard.



- 1. When assembling the belt to the pulley and rotating the motor after closing the side cover, confirm that the side cover does not interfere with the metal fitting of the belt.
- 2. Take care not to allow the belt to be clogged with oil when assembling it.


4-2. Subclass models

MB-1373	MB-1373-11
8, 16, 32 stitches	8, 16, 32 stitches



WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



- In order to install the attachment on the machine, you may have to remove button clamp mechanism or feed plate .
- Detach the snap ring from button clamp installing stud 3, and you will be able to remove button clamp mechanism assembly 1. Remove screw
 and you can remove feed plate 2.




The only feature that makes the difference between the attachment of MB-373NS and that of MB-377NS is button clamp lifting hook **6**.

Use	Flat bu	uttons	Shank I	buttons	Snaps
	Large-size	Medium-size	Gen	eral	Onapo
MB-1373 MB-1377	Z201	Z202	ZO	33	Z037
Schematic drawing	A A	A A	<u></u>		
Remarks	Button size :	Button size :	Button diameter :	Less than 16 mm	Snap size :
	A: 3 to 6.5 mm	A:3 to 5 mm	Shank size :		A:8 mm
	B : ø20 to ø28 mm	B : ø12 to ø20 mm	Thickness: 6 to 5 Width: 3 to 2.5 m		
Hee	Wrapped-arc	ound buttons	Metal buttons		
Use	First process	Second process	General	Stay button	Labels
MB-1373 MB-1377	Z041	Z035	Z038	Z039	Z044
Schematic drawing	T _A				
Remarks	Thread shank height			Common to Z041	Stitch width : 3 to 6.5 mm



WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



(INSTALLATION)

Remove both the button clamp mechanism assembly and the feed plate from the machine and install attachment 1 in place. Loosen screws 3 and adjust button clamp bracket 4 to permit the needle to come down in the middle of the needle slot in shank button adaptor 2. Attach button clamp feed plate 5 using screws 7 in the way that it permits the needle to come down in the middle of the needle slot in feed plate 6. Insert the top end of button clamp stud 3 into an opening in the jaw of the machine arm and fasten it by screw 9.

(ADJUSTMENT AND OPERATION)

- 1) Loosen screw **1**, let feed plate **6** recede 0.5 to 1.0 mm from the left end of button clamp jaw lever **2** and retighten screw **1**.
- 2) Set a button in place, loosen screws (3) and (4) and align shank button holding clamp (5) with the center of the button.
- 3) Shank button holding clamp (5) must give proper pressure to the button so that the button stays steadily in position while being sewn. Loosen a setscrew in thrust collar (6) and rotate the thrust collar until shank button holding clamp (5) provides proper pressure.
- 4) You may fix button clamp block **1** in a convenient position for operation.




- 1. When you fix the thrust collar, ensure that button clamp rotating shaft (6) does not play axially in its bracket.
- 2. Adjust lifting hook @ and stopper pin I) so that L-shaped lifting rod roller (9) does not come in contact with button clamp bracket ().
- (2) Attachment for the first process of wrapped-around buttons (Z041)



WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



(INSTALLATION)

Attach wrapped-around button foot 1 to the ordinary button clamp jaw levers using screw 2 and guide pin screw 3.

Align foot **①** with the jaw levers so that they permit a button to rest in the middle.

(ADJUSTMENT AND OPERATION)


Adjustment and operation are almost same as those for the flat buttons, but you must adjust the thread pull-off lever to provide more amount of thread in order to make the thread loose below the button for thread shank formation. (refer to "3-2. Adjustment of the thread pull-off lever", p.4)

(3) Attachment for the second process of wrapped-around buttons (Z035)



WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



(INSTALLATION)

Remove the button clamp mechanism assembly, button clamp pressure adjusting bar and feed plate from the machine and install attachment for the second process of wrapped-around buttons ①. When you install a Z035 attachment, you must remove also the L-shaped lifting rod.

Insert moving knife push-back spring 3, washer

- 4, cushion 5 and washer 4 in spring guide shaft
- ② in this order. Make certain that the stop-motion mechanism has completely engaged, and install the attachment assembly in place in the way that cushion ⑤ comes in close contact with the surface of the machine arm without play.

(ADJUSTMENT AND OPERATION)


- 1) Loosen screw 6 and adjust the thread shank length by moving guide (large) 7 and guide (small) 8 in line with the point of needle entry.
- 2) Set a button (tilt it slightly for easy insertion) and pass the thread as the arrow shows.
- 3) Set the lengthwise feed to "0".

(4) Attachment for snaps (Z037)



WARNING :

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.




(INSTALLATION)

Remove the button clamp mechanism assembly and the feed plate. Set both the crosswise feed and lengthwise feed graduated plates to "4 mm". Install snap clamp feed plate 1 in the way that the needle drops evenly at four corners of its square opening. Install snap attachment assembly 2 on the machine, place a snap on the snap clamp jaw levers and make sure that the needle drops accurately in each hole in the snap. If necessary, loosen hex head screws 3 and adjust the position accurately. Lastly, make sure that the concave section on the bottom face of snap clamp slide guide 4 accurately matches the convex section on snap clamp feed plate 1.

WARNING:

To protect against possible personal injury due to abrupt start of the machine, be sure to start the following work after turning the power off and ascertaining that the motor is at rest.



(INSTALLATION)

Remove both the button clamp mechanism assembly and the feed plate from the machine and install attachment in place. Loosen screws and adjust button clamp bracket to permit the needle to come down in the middle of the needle slot in metal button adaptor 2. Attach button clamp feed plate using screws in the way that it permits the needle to come down in the middle of the needle slot in feed plate into an opening in the jaw of the machine arm and fasten it by screw 9.

(ADJUSTMENT AND OPERATION)

- 1) Loosen screw (1), let feed plate (6) recede 1.0 to 1.5 mm from the left end of button clamp jaw lever (2) and retighten screw (1).
- 2) Set a button in place, loosen screws 1 and 2 and align metal button holding clamp 3 with the center of the button.
- 3) Metal button holding clamp (3) must give proper pressure to the button so that the button stays steadily in position while being sewn. Loosen a setscrew in thrust collar (1) and rotate the thrust collar until metal button holding clamp (3) provides proper pressure.
- 4) You may fix button clamp block (in a convenient position for operation.
 - When you fix the thrust collar, ensure that button clamp rotating shaft does not play axially in its bracket.
 - 2. Adjust lifting hook (1) and stopper pin (1) so that L-shaped liting rod roller (1) does not come in contact with button clamp bracket (1).

4-4. Motor pulley and belt

- 1) For this machine a single-phase or 3-phase 200 watts (1/4 HP) induction motor is used.
- 2) Use a V belt.
- 3) The sewing speed depends on the diameter of the motor pulley as listed below;

Hz	rpm Page 1	Motor pulley part No.	E CO
Trybothe william galvo	1500	40038291	ø 76
50	1300	40038298	ø 64.5
Philippes	1500	40038298	ø 64.5
60	1300	40042229	ø 57

- ★ The pulley of 50Hz and 1,300 rpm is in common with that of 60Hz and 1,500 rpm.
- ★ The rotating direction of motor is counterclockwise when viewed from the motor pulley side. Be careful not to rotate in reverse direction.
- ★ When replacing the motor pulley and changing the sewing speed from 1,300 rpm to 1,500 rpm and vice versa, be sure to re-adjust the position of the stop-motion. (Refer to "Adjusting the position of the stop-motion", p.8.)

5. TROUBLES AND CORRECTIVE MEASURES

TROUBLES	CAUSES	CORRECTIVE MEASURES
. Thread breakage	The yoke slide does not move in the correct way.	 Adjust the timing of forward, backward and sideways of the yoke slide.
		Properly adjust the tension lever.
essa melhanden (ina		Make the thread release timing slightly earlier.
IN THE STREET	Lifting amount of the button clamp jaw unit is excessive.	 Adjust the lifting amount of the button clamp jaw lever to 8 mm.
er albeen diraminell om nutole albeen grade a	The thread nipper catches the thread. The nipper has been improperly adjusted. (The clearance is too small.)	Adjust the position of the nipper bar block.
enalo beni gajejo noma	The needle does not enter the center of the holes in the button.	Adjust the button clamp jaw lever holder.
rai Jote albeen ent to e	The needle is too thick for the diameter of the hole in the button.	Replace the needle by a thinner one.
The machine forms a seam after it has run for a	The thread pull-off lever has been improperly adjusted.	 Adjust the thread tension guide on the face plate so that it provides a lower tension.
while instead of forming it from the start of sewing.	② Tension of the thread tension guide on the face plate is excessive.	Properly adjust the tension lever.
3. Buttons are not sewn tightly	The yoke slide does not move in the correct way.	 Adjust the timing of the motion of the yoke slide at each end.
	The thread tension post No. 2 fails to release the thread at correct timing.	Make the thread release timing slightly later.
	The thread tension post No. 2 does not give sufficient tension.	Tighten the tension nut of tension post No. 2.
	4 The needle does not enter the center of the holes in the button.	Adjust the button clamp jaw lever holder.
	5 The work pressing force is too high or too low.	Adjust the work pressing force properly.
4. The last back-tack stitch	1 The tension lever has been improperly adjusted.	Properly adjust the tension lever.
is poorly tensed.	② Timing of the knot-tying plate is incorrect.	Advance the timing of the knot-tying plate. (Adjustment of the knot-tying notch)
at vilable valg for year	3 The nipper has been improperly adjusted. (The clearance is too large.)	Adjust the nipper with the nipper bar block.
5. The first stitch trails relatively long thread from the right side of the button	The thread pull-off lever does not work properly.	Adjust the thread pull-off lever by the nipper bar block (rear).
6. Thread trimming failure in the state of stop-	① The thread tension post No. 2 fails to release the thread at correct timing.	give more tension to the stitches.
motion	② The needle hits the edge of the holes in the button.	Adjust the button clamp jaw lever holder.
	· 3 The thread nipper fails to press the thread.	Adjust the nipper bar block.
been c	4 The work pressing force is too high.	 Adjust the work pressing force by the pressure adjusting nut.
7. Thread trimming failure	The moving knife does not separate the thread on the fabric with its separation nail.	Adjust the position of the moving knife.
	② The needle does not enter the center of the holes in the button.	Adjust the button clamp jaw lever holders.
	③ The last stitch skips.	Adjust the looper.
	The moving knife thread separation nail is too high or too low.	separation nail.
8. The needle thread is cut in two places on the		 Adjust the position of the moving knife when the machine is in the stop-motion state.
wrong side of the fabric	high or too low.	
Button trails too long thread after thread trimming.	 Timing of the moving knife motion is wrong. Lifting amount of the button clamp jaw unit is 	 Adjust the position of the moving knife. when the machine is in the stop-motion state. Adjust the lifting amount of the button clamp jaw
	excessive.	lever to 8 mm.
10.Length of thread remaining, after thread	① Position of the moving knife is not correct.	Adjust the position of the moving knife when the machine completes stop-motion. (10 to 11 mm)
trimming, on the wrong side of the material varies.	② Lifting amount of the button clamp jaw unit is excessive.	 Adjust the lifting amount of the button clamp jav lever to 8 mm.


Single Thread, Chainstitch Button Attaching Machine 高速単糸環縫ボタン付ミシン 2.

1373 1377

PARTS LIST

1. BUTTON CLAMP MECHANISM COMPONENTS


ボタンつまみ関係



REF. NO N	OTE PART NO.	DESCRIPTION		Qty
1	260-26856	PICK-UP DEVICE ASM.	プマミソウチ(ケブコ・ウ)	1
2	400-41058	BUTTON CLAMP LIFTING HOOK	サマミソウチヒキアケ・フック	(1)
3	SS-7150940-SP	SCREW 15/64-28 L=9	マルヒラネシ 15/64-28 L=9	(1)
4	SS-9621413-SP	SCREW 3/16-32 L=13.5	ロッカクオ ルト 3/16-32 L=13.5	(2)
5	WP-0501016-SD	WASHER 5X10.5X1	ሂታታ ታ ት ቅ 5 X10.5X1	(2)
6	260-25502	BUTTON CLAMP HOLDER	プマミソウチトリプケタ・イ	(1)
7		SCREW 9/64-40 L= 3.5	マルヒラネシ 9/64-40 L=3.5	(1)
8	SD-0550301-SP	HINGE SCREW D=5.5 H=3	タ*ンネグ* D=5.5 H=3	(1)
9	260-25403	JAW LEVER HÖLDER	す。タンプマミアシトリプケタ・イ	(1)
10	SD-0550181-SP	HINGE SCREW D= 5.50 H= 1.8	タ・ンネツ・ D=5.5 H=1.8	(1)
11	260-25809	CLAMP SCREW A	ヒラキレハ・ートメネシ・(A)	(1)
12	260-25700	SNAP FASTENER CLAMP STOP LEVER	プマミアシヒラキレハ・-	(1)
13	260-26005	NUT	* タンカ・イト・アシトメネシ・(B)	(1)
14	260-25908	BUTTON CLAMP SLIDE	** タンカ* イト* アシ	(1)
15	260-26609	BUTTON CLAMP STOP PIN	プマミアシヒラキヒ・ン	(2
16	260-26104	BUTTON CLAMP LEVER JAW (LEFT)	ショウオ・タンヨウオ・タンプマミアシ ヒタ・リ	(1
17	260-26203	BUTTON HOLDING SPRING, LEFT	ショウオ・タンヨウオ・タンプマミイタハ・ネ(ヒ	(1)
18	SD-0640391-TP	HINGE SCREW D= 6.35 H= 3.9	タ・ソネシ D=6.35 H=3.9	(2)
	SS-7090410-SP	SCREW 9/64-40 L= 3.5	マルヒラネシ 9/64-40 L=3.5	(1)
19	260-26708	BUTTON CLAMP SPRING	* タンプマミアシハ・ネ	(1
20		BUTTON CLAMP LEVER JAW RIGHT	ショウオ・タンヨウオ・アングマミアシ(ミキ・)	(1
21	260-26302	BUTTON HOLDING SPRING, RIGHT	ショウオ・タンヨウオ・タンプマミイタハ・ネ(ミ	(1
22	260-26401	SCREW 15/64-28 L=9	マルヒラネシ 15/64-28 L=9	(1
23	SS-7150940-SP	BUTTON CLAMP_PRESSURE_ADJUSTIN	オサエアプリョクチョウセプ本・ウ	1
24	400-40938	PRESSURE ADJUSTING SPRING	オナエチョウセッハ・ネ	1
25	260-27102		מאלילים M6	2
26	NM-6060001-CP		ゴド. ル. ート.	1
27	260-27409	FINGER GUARD	ハ・ネウケイタ	1
28	400-41069	SPRING_HOLDING_PLATE	サマミソウチトリッケシ ク	1
29	260-25205	HINGE PIN	プマミソーチ トリプケシ・ク トメワ	1
30	B2541-372-000	SNAP RING		-
31	NM-6060001-CP	NUT M6	ロッカクナット M6	1
32	400-40937	PICK_UP_DEVICE_STOPPER_PIN	ブマミソウチストッハ・ヒ・ソ	-

2. ARM & MISCELLANEOUS COVERS COMPONENTS


アームベッド関係



1 2		400-38426 SM-4040855-SP	FACE_PLATE_COMPL. SCREW	メンイタケブコ・ウ	1
3		260-21600	TENSION SPRING	ታ^` ネ ジ	4
4		260-32003	NIPPER RELEASING STUD	ニカル・ーイトコルメド・ハル・オ	1
5		SM-6040650-TF	SCREW	ニッハ・ーイトユルメホ・ウ ヒラネシ・M4 L=6	1
6		260-31203	THREAD GUIDE NO.4		1
7		260-31203	THREAD TENSION NO.3 ASM.	g* 141h7\tag{7}	1
8		260-31302	TENSION ADJUSTING BASE NO.3	タ・イ3イトチョウシ(クミ)	1
9		260-31302	THREAD PRESSER PLATE	タ・イ3イトチョウシトリプケタ・イ	(1)
0		260-31500	TENSION SPRING 5	ハリイトオサエイタ ハリイトチョウャル・テロ	(1)
1		260-31609	THREAD TENSION STUD	ハリイトチョウシハ・ネB	(1)
2		260-31708		タ・イ3イトチョウシスタット・	(1)
3			THREAD TENSION NUT	タ・イ3イトチョウシブマミ	(2)
		RE-0320000-K0	E-RING 3.2	Eカ タトメワ 3.2	1
4		SM-4040855-SP	SCREW	ナペネジ	8
5	1	TA-2050406-R0	RUBBER PLUG	トメセン	1
6		400-40931	SIDE_COVER_RIGHT	ミキ・ソクメンカハ・ーカンセイ	1
7		CM-3013000-01	SAFETY LABEL	トウフ・チュウイアンセ・ンシール(33)	1
8		400-40932	SIDE_COVER_LEFT	ヒタ・リソクメンカハ・ーカンセイ	1
9		SM-6083042-CH	SCREW M8 L=30	ロプカクアナホ・ルト M8 L=30	4
.0		260-33704	STOPPER	イトムスと・ウテ・ストッハ・-	1
1		SM-6050800-SP	SCREW M5 L=8	ヒラネシ M5 L=8	2
2		260-11205	GUIDE PIN	アームへ、 ットケブコ、 ウカ、 イト、 ヒ、 ン	2
3		400-38483	SET_SCREW	アームヘ・ットトリッケネシ・	1
4		400-38431	BED_OIL_SHIELD	v. ルトコギ、ーン、ハ	1
15		SM-8060610-TP	SCREW	トメネシ M6 L=6	1
6		400-41022	BUTTON_TRAY_ASM.	オ・タンウケサ・ラクミ	1
	#01	260-22608	CAM INDICATING PIN A	オクリカムイチキメシシンA	2
	#01	260-22707	CAM INDICATING PIN B	オクリカムイチキメシシンB	2
29		WS-0650389-KP	SPRING WASHER 6.5X14.0X17	ሶ* ት ታ* ታ * ት 6.5X14X1.7	1
0		400-38425	SIDE_COVER_LEFT	サイト・カハ・ーヒタ・リ	1
31		400-38430	LOOPER_COVER	ルーハ・一カハ・一	1
2		400-41067	SIDE_COVER_SPRING	ソクメンカハ・ーハ・ネ	2
13		SM-6040600-SP	SCREW M4 L=6	ヒラネシ M4 L=6	2
4		SM-4040855-SP	SCREW	ታ ላ *	2
15		400-38173	OIL_DRIP_FELT	キュウュフェルト	1
6		SD-0600277-TP	SHOULDER SCREW D=6 H=2.7	タ・ンネシ D=6 H=2.7	1
7		400-38424	SIDE COVER RIGHT	サイト・カハ・ーミキ・	1
18		400-40936	SIDE COVER HINGE SHAFT RIGHT	ソクメンカハ・ーシ・クミキ・	2
39		400-40935	SIDE_COVER_HINGE_SHAFT_LEFT	ソクメンカル・ーシ・クトタ・リ	1
0		SM-8060612-TP	SCREW M6 L=6	トメネシ M6 L=6	1
11		400-38446	MACHINE SUB BASE	^* y\\Jy754. 1	1
2		SM-8060612-TP	SCREW M6 L=6	トメネシ M6 L=6	1
3		400-38471	SUSPENSION SCREW B	シタイトキリ サト・ウイタ リンクハ・ネカケB	1
14		400-54729	ASSY SAFETY PLATE	721 LAD 21 712 7774 4770	1
45		400-54730	SAFETY PLATE INSTALLING BASE	メネコ・カハ・ートリプケタ・イ	(1)
46		260-37200	SAFETY PLATE	7ンセ・ソフ・レート	(1)
47		SM-4040655-SP	SCREW M4 L=6	ナヘ・コネシ・M4 L=6	(2)
18		WP-0430800-SD	WASHER M4	ヒラサ・カ・ネ コカ・タマル M4	(2)
19		TA-1250406-R0	RUBBER PLUG D=12.5 L=4	トメセン D=12.5 L=4	2
50		PS-0500102-KH	SPRING PIN 5.0X10	スプ・リング・ド・ハ 2X10	1
		NOTE (注記)	#01SELECTIVE PARTS	選択部品	

3. LOOPER SHAFT MECHANISM COMPONENTS


ルーパー軸関係



1 2	CS-079072A-TH	THRUST COLLAR ASM.	スラストウケ クミ	
	CS-0790721-TH	THRUST COLLAR D=7.94 W=7	スラストウケ D=7.94 W=7	(
3	SS-7090620-TP	SCREW 9/64-40 L=6.1	マルヒラネシ 9/64-40 L=6.1	(
4	SM-6040800-SP	SCREW	ヒラネシ・	
5	400-38484	NEEDLE_GUARD	ハリカ・イト・	
6	260-13607	POSITIONING FINGER YOKE SLIDE	イトヨセササエ	
7	SM-1040950-TP	SCREW M4 L=9	サラコネシ M4 L=9	
3	260-13409	YOKE SLIDE INSERT	イトヨセササエタ・イ	
9	260-13805	YOKE SLIDE	1h3t	
)	400-38400	ASSY_LOOP_POSITIONING_FINGER_L	イトヨセセ・ソコ・ウテ・クミ	
	400-38403	LOOP_POSITIONING_FINGER_CAM_RO	イトヨセカムコロ	(
2	SD-0640246-SP	HINGE SCREW D=6.35 H=2.4	タ・ソネシ D=6.35 H=2.4	
3	SM-8061010-TP	SCREW	トメネシ M6 L=10	
3.12	B1241-377-0B0	THROAT PLATE SET	ハリイタ(クミ)	
	B1241-377-0A0	THROAT PLATE ASM.	ハリイタ(ケザコ・ウ)	(
	B2703-377-0A0	THREAD BIND PLATE ASM.	イトムスヒ・イタ(ケブコ・ウ)	(
	B2702-377-000	THREAD BIND SUPPORT PLATE	イトダンド・キチェイタ	(
1	B2410-373-000	COUNTER KNIFE	コテイメス	(
	SS-7080310-SP	SCREW 1/8-44 L= 3.0	マルヒラネツ・1/8-44 L=3	(
)	B2406-373-0A0	MOVING KNIFE ASM.	ト・・メス クミ	(
	SD-0600095-TH	HINGE SCREW D= 6 H= 0.85	タ・ンネツ・ D=6 H=0.85	(
2	400-41106	ASSY_LOOP_POSITIONING_FINGER_C	イトヨセサンカクカムクミ	
3	260-03103	LUOP POSITIONING FINGER CAM	イトヨセサンカクカム ~	(
1	SS-8110410-TP	SCREW 11/64-40 L= 3.5	トメネシ・11/64-40 L=3.5	(
5	400-38482	ASSY CAM AND LOOPER SLEEVE	ルーハ・ートリッケシ・ククミ	,
3	260-15503	CAM AND LOOPER SLEEVE	ルーハ・ートリッケシック	(
7	SS-8150410-TP	SCREW 15/64-28 L= 4.0	トメネシ・ 15/64-28 L=4	(
3	B1228-372-000	LOOP POSITIONING FINGER CAM RE	1hathA	,
	SS-8110310-SP	SCREW 11/64-40 L= 2.8	トメネツ・11/64-40 L=2.8	
)	260-15305	LOOPER SHAFT BUSHING FRONT	N-N>. クムエメタリ	
	SM-8061010-TP	SCREW	トメネን M6 L=10	
	400-38111	LOOPER SHAFT	N-N3. 7	
3	CS-111101K-SH	THRUST COLLAR ASM. D=11.11 W=1	スラストウケ D=11.11 W=10クミ	
	CS-1111019-SH	THRUST COLLAR D=11.11 W=10	スラストウケ D=11.11 W=10	(
,	SS-8660512-TP		トメネシ 1/4-40 L=5	(
5	SS-8660512-TP	SCREW 1/4-40 L=5	トメネツ・1/4-40 L=5	(
7	B1224-372-0A0	LOOPER SHAFT DRIVEN GEAR ASM.	\$3. V4. VA B 45	,
3	SS-8660612-TP	SCREW 1/4-40 L=6	トメネジ 1/4-40 L=6	(
	B1215-372-A00	THRUST BALL BEARING	ルール・シ・ク スラスト ヘ・ブリング・	,
	260-13102	LOOPER SHAFT BUSHING REAR	ルール・ーシ・クウシロメタル	
	B1221-373-NAO	WORM WHEEL ASM.	ウオームハク・ルマ クミ	10 10
2	B1221-373-NA0	WORM	ウオーム	
		SCREW 1/4-40 L= 7.0	リオーム とラネシ・1/4-40 L=7	(
3	SS-6660712-TP B1220-372-000			(
4			ウオームハク・ルマ	(
5	SS-8660612-TP	SCREW 1/4-40 L=6	トメネタ・1/4-40 L=6	(
6	B1239-372-000		V-V.	
7	SM-1040950-TP	SCREW M4 L=9	サラコネシ M4 L=9	

4. NIPPER & THREAD TENSION PARTS COMPONENTS


糸調子、ニッパー関係



1	SM-4061255-SP	SCREW M6 L=12	ナヘ・ネラ・ M6 L=12	
2	400-38205	NEEDLE BAR GUARD	νηφ. φμν. − Σν γλ μο Γ=17	1
3	SD-0791276-TP	SHOULDER SCREW	タ・ソネシ・ D=7.94 H=12.7	1
4	NM-6030001-SN	NUT	ロブカクナット	2
5	260-20602	NUT	ニッハ・ーイトコルメヒ・ンナット	ī
6	260-00950	NIPPER COMPL.	ニブハ・- (ケブコ・ウ)	1
7	260-20503	LOOPER SHAFT BUSHING REAR	ニッハ・ーイトユルメヒ・ソ	1
8	400-41077	NIPPER_BAR_BLOCK_SPRING	ニスレ、ートンレ、カレ、タ	1
9	400-38492	NIPPER_BAR_BLOCK_SPRING_SCREW	ニナル・ーヒナル・リル・ネシ・ク	1
11	SD-0402001-TP 260-20404	HINGE SCREW D=4 H=20	タ・ソネグ・ D=4 H=20	1
12	260-20305	NIPPER SLIDE BLOCK SPRING NIPPER BLOCK	ニッハ・ーカクコ・マハ・ネ	1
13	SD-0791506-TP	SHOULDER SCREW D=7.94 H=15	ニッハ・ーカクコ・マ	1
14	400-38476	THREAD PULL OFF LEVER ASM	タ・ンネク・ D=7.94 H=15 イトチョウセプレハ・-クミ	1
15	SD-0790806-TP	SHOULDER SCREW D=7.94 H=8	タ・ソネシ・ D=7.94 H=8	1.
16	260-00455	NIPPER BAR ACTUATING LEVER ASM	サンカクイタ(ケブコ・ウ)	1
17	260-20206	THREAD GUIDE PIN	イトアンナイ本・ウ	2
18	260-19406	NIPPER BAR BLOCK SPRING PIN	ニュン、ートュン、カン、タト、ブ	1
19	SM-6040800-SP	SCREW	ヒラネシ・	1
20	WP-0450801-SP	WASHER	ヒラザ・カ・ネ	2
21	260-19307	NIPPER BAR BLOCK	באַר, -שלף. לבל	1
22	260-19208	TENSION LEVER ROCKING PIECE	イトチョウシレハ・-ヨウト・ウコマ	1
23	400-38479	NIPPER_BAR	イトチョウシチョウセプカン	1
24	SM-6040800-SP	SCREW	ヒラネシ・	1
25	400-38208	TENSION_POST_ASM_NO.2	タ・イニイトチョウシ_クミ	1
26 27	400-38214	TENSION_NUT	イトチョウシナット	(1)
28	229-21407 260-19901	ROTATION STOPPER	イトチョウシサ・ラカイテント・メ	(1)
29	260-19901	THREAD TENSION SPRING THREAD TENSION DISK PRESSER	タ・イ2イトチョウシハ・ネ	(1)
30	260-05207	THREAD TENSION DISK NO. 1	イトチョウシサラオテエ タ・イ1イトチョウシサ・ラ	(1)
31	400-38210	TENSION POST NO.2	\$' 111\f30\f3 7	(2)
32	260-19802	TENSION_RELEASE_PIN	チョウシサラウカシネ・ウ	(1)
33	NM-6060001-CP	NUT M6	ロッカクナット M6	(1)
34	PS-0300162-KH	SPRING PIN 3X16	77. 174. F. 7 3X16	1
35	SN-6040800-SP	SCREW	ヒラネシ・	i
36	WP-0450801-SP	WASHER	ヒラチ・カ・ネ	1
37	260-19109	THREAD TENSION RELEASING LEVER	チョウシサラウカシイタ	1
38	400-38404	ASSY_THREAD_TENSION_NO.1	タ・イイチイトチョウシクミ	1
39	400-38408	THREAD_TENSION_NUT	イトチョウシナット	(1)
40	260-05306	FIRST THREAD TENSION SPRING	タ・イ1イトチョウシハ・ネ	(1)
41	260-05207	THREAD TENSION_DISK_NO.1	タ・イ1イトチョウシサ・ラ	(2)
43	400-38405 260-19505	THREAD_TENSION_POST_NO.1	タ・イイチイトチョウシオ・ウ	(1)
44	260-19505	THREAD GUIDE THREAD GUIDE NO.1	タ・イ1イトチョウシサラアンナイオ・ウ	1
45	NM-6040002-SN	NUT M4	9 11117771	1
46	SM-4061255-SP	SCREW M6 L=12	ログカクナプト M4X0.7 2シュ	1
47	400-38396	NIPPER BAR BEARING BLOCK	ナヘ・ネツ・M6 L=12	1
48	400-38206	ADJUSTING SCREW	イトチョウシチョウセプカンアンナイタ・イ イトチョウシチョウセプカンアンナイシ・ク	1
49	WP-0550800-SP	WASHER 5.5X10X0.8	kラサ か ネ 5.5X10X0.8	1
50	SM-7051460-TP	SCREW M5 L=14	マルヒラコネシ M5 L=14	1
51	SM-6051400-SP	SCREW	ヒラネシ・	1
52	260-19000	THREAD TENSION SPRING	イトチョウシチョウセブカンヒッハ・リハ・ネ	1
53	400-38207	NIPPER_BAR_SPRING SCREW	イトチョウシチョウセブカンヒッハ・リハ・ネカ	i
54	WP-0450846-SP	WASHER	۲ ۶۶. ۳. ۶	i
55	SM-9061403-CP	SCREW M6 L=14	מאלים אין מאלים	i
56	NM-6060001-SE	NUT M6	ロッカクナット M6 1シュ	1
57	260-21105	THREAD GUIDE	イトチョウセブイトアンナイ	1
58	400-38320	LEVER	イトラメレハ・-	1
59 60	SM-6040600-SP	SCREW M4 L=6	ヒラネシ M4 L=6	1
	WP-0501016-SD	WASHER 5X10.5X1	とラサ・カ・ネ 5X10.5X1	1

5. FEED PLATE COMPONENTS

送り関係




29	# 2957 'PC	28			FEED_STUD_A		
257 #203 400-41055	1	255 203 400-41055 FEED STUD 8 2797 78	4	400-38453 B1161-227-000	CROSSWISE_FEED_LEVER RIVET	ヨコオクリレハ・- トメヒ、ヨー(キ、ハイロ)	1 2
28	# 2957 'PC	28	6 #03	3 400-41055	FEED_STUD_A		1
10	************************************	10	7 #03	3 400-41056	FEED_STUD_B		
90		1			FEED STUD C	3/ 111 23448(f191 37)	
### ### ### ### ### ### ### ### ### ##	57オグリリのプラロセフコマ 57オグリル ~ (1 57オグリル ~ (1) 12オグリル ~ (1) 12オグリル ~ (1) 12 17 17 18 18 18 18 18 18 18 18 18 18 18 18 18	### ### ##############################				r54. 4. 3 2X10.2X1	2
2 400-38432 FEED LEVER SLIDE 57879197791 3 400-38432 FEED LEVER L 57879197791 4 400-38432 FEED LEVER L 37879197791 5 400-41061 FEED LEVER R 37879197791 5 5 400-41061 FEED KNOB GUIDE PLATE 19787947974 6 SN-9050813-SE SCREW MSAO 3 L-8 197977 kM 1879 8 201 400-38438 PLATE BASE (MB-1377) 7978748197 9 202 400-38313 GRADUATE PLATE (MB-1377) 79787948197 9 202 400-38313 GRADUATE PLATE (MB-1377) 82787948197 1 400-38314 GRADUATE PLATE (MB-1373) 829745(MB-133) 82	37キグラル・ (1 ココオクラル・ (1 カフラル・ (1) カフラルフ・ (1) カフラルフ・ (1) カフラルフ・ (1) カフラルフ・ (1) カフラルフ・ (1) カフラルフ・ (1) カファルフ・ (1) カファルフ・ (1) カン・ (2			LENGTHWISE FEED LEVER ARM	タテオクリレハ'ーケブコ'ウス'ケンチョウ	
1	コスタラリル・ (1) カリテカケナサマシナイト・49 フラカア・5ト 地500 8 L-8 ラテカアシスを19トランタ・18 ラテカツラスを19トランタ・4 カラカツラスを19トランタ・4 オーチャイタ(MB-1377) カリテカア・5ト 18 カラカツラスを19トランタ・7 オー・コカア・加く 1-6 ナー・コカア・加く 1-6 ナー・コカア・加く 1-6 ナー・コカア・カー・カー・カー・カー・カー・カー・カー・カー・カー・カー・カー・カー・カー・	10		400-38439	LENGTHWISE_FEED_LEVER_SLIDE		
AUG-4105 FEED KNOB GUIDE PLATE	1999年のセサワマミナイト・49 ロサラケイ N MS 10.8 L-8 9テカクリメモリイタトリファケイ B 9テカクリメモリイタトリファケイ B 9テカクリメモリイタトリファケイ C メモリイタ(MB-1373) メモリイタ(MB-1373) メモリイタ(MB-1373) メモリイタ(MB-1373) メモリイタ(MB-1373) メール コナー M L-6 ナース オーク カム アーク カム アーク カム アーク カム アーク カム アーク カストウナウト スストウナー スストウナー カンテーク カステーク	Second Color					
SW 9950813 - SE	ラテオツメモリイタトサッケ イ B ラテオツメモリイタトリフナケ イ オモリイタ(MB-1373) スモリイタ(MB-1373) オートリイタ(MB-1373) オートリートーーーーーーーーーーーーーーーーーーーーーーーーーーーーーーーーー	SW 1950813 - SE				オクリチョウセプラマミカ・イト・イタ	
77	ラテカクラスをリア・トリカフか イ メモリイ女(MB-1373) メモリイ女(MB-1377) メアリイ女(MB-1377) メアリー・ ナー・コカフ・ M4 L=6 ラテカプリチョウセリル・ー ラテカプリチョウセリル・ー イ フィカプリチョウセリル・ー イ フィカプリチョウセリル・ー イ フィカプリチョウセリル・サーイ ナーンゴーオウラム(X) セーンゴーオウラム(X) セーンゴーオウラム オンプースクラム(X) オンプースクラム(X) フィカプースクラム(X) スストラウラー スストラウラー スストラウラー スストラウラー スストラー カルプークスタム(スキー) トメカプークスタム(スキー) トメカプークスタム(スキー) トメカプークスタム(スキー) トメカプークスタム(スキー) トメカプークスタム(スキー) トメカプークスタム(スキー) トメカプークスタム(スキー) アプード・メアエムト オクリターンストラー アプード・メアエムト オクリターンストラー アプード・メアエムト オクリターンストラー オクリターンストラー アプード・メアエムト オクリターンストラー オフ・アナーストー アプード・メアエムト オクリターンストラー オフ・アナーストー アプード・メアエムト オクリターンストー オフ・アナーストー アプード・メアエムト オクリターンストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー アプード・アエムト オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナーストー オフ・アナー オフ・アナーストー オーター オー オーター オーター オーター オーター オーター オーター オーター オーター オーター オーター オー オーター オー オー オー オー オー オー オー オー オー オ	7			SCREW M5X0 8 L=8	ロプカクオ' Aト M5X0.8 L=8	
10	大学・イタ(WB - 1373)	10	7 #02	2 400-42279	PLATE_BASE_(MB-1373)		
201 400-38314 GRADUATE PLATE (NE-1377) AE+4/4 (NE-13) 1	ポリイタ(MB-1377) オリチョラセリル' - ナ・コカ' M5 L=8 ラテカリチョウセリル' - ナ・スケ M5 L=8 ラテカリチョウセリル' - カ・イ オケ M5 L=8 ラテカリチョウセリル' - カ・イ オケ M5	AU			PLATE BASE (MB-1377)	4777774490 757777 1	
1	** ** ** ** ** ** ** ** ** ** ** ** **	1				メモリイタ(MB-1377)	
SM-4050855-SP SCREW 1	ティッカン 15 L=8 ラオアリキリカエマミ ラオアリキリカエマミ ラオアリキリカセナル・ライ オンティ オンティン 16-35 H=9.7 ホンティンスラム(X) センエオツリカム カンティスタム(X) ザリ ラファフリカム センエオツリカム メーンスティンステム ディステーター。 スストラファーストーラー。 カンティスタム(ミナー) トスオン・タバスと28 L=13.5 フストラファーストーラー。 オンティンストラファーストーラー。 オンティンストラファーストーラー。 オンティンストラファーストーラー。 オンティンストラファーストーラー。 オンティンストーター。 オンティンストーター。 オンストーター。 オンティンストーター。 オンティンストーター。 オンストーター	SH-4050855-SP SCREW 1.5 SCREW 1.5 SCREW 1.5 SP SCREW 1.5 SP SCREW 1.5 SP SCREW 1.5 SP SP SP SP SCREW 1.5 SP SP SP SP SP SP SP S			HANDLE_AND_INDICATOR_SPRING	オクリチョウセグレハ・-	
Same	ラテオプラリカエアマミ ラテオプラリテコセナル・一・ディ デンステ D=6、35 H=9.7 カムデ ク オンデ オクラム(X) センゴ オクラム(X) センゴ オクラム(X) センゴ オクラム(X) センゴ オクラム(X) オンプ メタム(X) オンプ オクラム(X) スストラクラミ スストラクラミ カムデ アメン・ランスと E=13.5 スストラクラ トメネデ タンスと E=13.5 スストラクラ トメネデ タンスと E=13.5 スストラブ トメネデ スペーテータル(ステース) トメネデ タンスと B=13.5 モデスデ M5 L=8 アブ・ディーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート オフ・アナーストート	Second		SN-4040655-SP	SCREW M4 L=6	ナヘ・コネケ・ M4 L=6	
100 100	ラデオアリチのシャリハ・ーティ オンステ しゅう。35 トロ・フ オンステ しゅう。35 トロ・フ オンテ ・	10		SM-4050855-SP			
SUBJECT SHOULDER STREM D= 5.25 H=9.7 3 / 747 D=6.	3' ソネジ D=6、35 H=9、7 カネ' ? ***********************************	SD-0640976-TF					
A00-38444	### ### ##############################	ABO-98-944 CAM SHAFT SHAFT ABO-98-944 CAM SHAFT CAM SH					
400-41032	+ 'ya' 47954 (25' 7) ## 'ya' 47954 (25' 7) ## 'ya' 79754 (25' 7)	### 400-41032 LENGTHMAISE_FEED CAM ### 2756-373-000-A ### 1008					
## ## ## ## ## ## ## ## ## ## ## ## ##	\$\frac{1}{2}\frac{1}{2	## ## ## ## ## ## ## ## ## ## ## ## ##		400-41032		t. ハコ. ギャカサヤ(X)	
AUC-41033	#37月7月3日 セソコ オリカー セソコ オリカー オッカナ りゅら、35 H=4・8 トメカナ 9/32 - 28 L=13・5 スラストウクタミ スラストウクタラ スペーラ カカナ 9/32 - 28 L=13・5 モラステ サルラル(キャ) トメカナ 9/32 - 28 L=13・5 モラステ N5 L=8 アプラト・メフェルト オリタ フォラ・メフェルト オリタ フォラ・メフェルト オリタ フォラ・フェルト	AUG-41035			LONGITUDINAL FEED CAM	チ. ハコ. オクカカヤ	
## ## ## ## ## ## ## ## ## ## ## ## ##	* 'Y' #7##A * 'Y47' De6.35 H=4.8 hxth '' 9/32-28 L=13.5 737h-979 hxth '' 745h(\$\frac{2}{2}) hxth '' 745h(\$\frac{2}{2}) hxth '' 9/32-28 L=13.5 577' htt. ha hyth '' 75h ht. ha hyth '' 75h '' 75h hyth '' 75h '' 75h	### ### ### ### ### ### ### ### ### ##			CAM SHAFT BUSHING, LEFT	カムラ・ケメタル(ヒタ・リ)	
SP-0640486-TP	\$'\\partial_3'\partial_3'\\partial_3'	SD-0640486-TP SHOULDER SCREW D=6.35 H=4.8 3* ½7* D=6.35 H=4.8 D1 SS-8681412-TP SCREW 9/32-28 L=13.5 5.2 D2 400-40964 THRUST COLLAR 7.3 TS-8060552-TP SCREW 8/6.2 5.2 D3 400-42081 SPACER 7.2 D4 400-42081 SPACER 7.2 D4 5.2 5.2 5.2 D5 5.3 5.4 5.2 D6 5.3 5.4 5.2 D6 5.4 5.4 5.2 D7 5.4 5.4 5.4 D8 5.4 5.4 5.4 D8 5.4 5.4 5.4 D8 5.4 5.4 D9 5.4 D9 5.4 D9 5.4 D9 5.4 5.4 D9 5.4 5.4 D9 5.4 5.4 D9				ラ ュウオクリカム	
### ## ## ## ## ## ## ## ## ## ## ## ##	hxty 9/32-28 L=13.5 737h9992 737h997 hxty xx - 9 xx - 1 xx - 2 xx - 2 xx - 3	### ### ### ### ### ### ### ### ### ##			LONGITUDINAL FEED CAN A	6. 73 10. NAV	
30	7374-9792 7374-979 747-97 1477-7946(247) 747-9732-28 L=13.5 77-74-74-8 77-74-74-8 77-74-74-8 77-74-74-8 77-74-74-8 77-74-74-8 77-74-74-8 77-74-74-8 77-74-74-8 77-74-74-8 77-74-74-8 77-74-74-8 77-74-8 7	101 S300818 11 TRRUST COLLAR ASSY 3731.0992 102 400 - 40964 TRRUST COLLAR ASSY 3731.0992 103 400 - 40964 TRRUST COLLAR ASSY 3731.09 104 400 - 2008 TRRUST COLLAR ASSY 3731.09 105 400 - 2000 TRRUST COLLAR ASSY 3731.09 105 400 - 2000 TRRUST COLLAR ASSY 3731.09 106 400 - 2000 TRRUST COLLAR ASSY 3731.09 107 108 400 - 2000 TRRUST 400 - 2000 108 400 - 41045 TRRUST COLLAR ASSY 400 - 41045 108 400 - 41045 TRRUST COLLAR ASSY 400 - 41045 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 109 1				144 9/32-28 L=13 5	
AU0-4095 THRUST_CULLAR X7A >97	スタストラウ トメネタ・ スペーサ カカツ アメラル(ミヤ・) トメネタ・ 9/32-28 L=13.5 モラネタ・ M5 L=8 アプ・ラナ・ガマエムト オクリタ・ンネタ・フェルト ユラリケ・・ フェルト	100-40981					
SM-8080552-TP SCREM NG L=5 Sx32" ## ## ## ## ## ## ##	hx42' (7.7 + 7.8 + 7.7 + 7.8 + 7.7 + 7.8 + 7.7 + 7.8 + 7.7 + 7.8 + 7.7 + 7	SM = 9050552-TP SCREW NG L=5 Nx + 7 #01 400-42081 SPACER A					
3 #01 400-42081 SPACER 7 # *** *** *** *** *** *** *** *** ***	スペーチ カカプ アメラル(ミギ・) トメネケ・9/32-28 L=13.5 でラネリ 第5 L=8 アプ・デ・オフェルト オクリデ・ンネケ・フェルト ユラツ 0.4	#01 400-42081 SPACER A.*- 260-22400 CAM SHAFT BUSHING.RIGHT hbs?y494(\$\frac{1}{2}\$) \$260-22400 CAM SHAFT BUSHING.RIGHT hbs?y494(\$\frac{1}{2}\$) \$260-22400 CAM SHAFT BUSHING.RIGHT hbs?y494(\$\frac{1}{2}\$) \$260-22400 SURPH 96-228 L=13.5 \$260-228 L=13.5 \$260-					(
260-22400 CAM SHAFT BUSHING RIGHT \$\frac{1}{2}\tau^2 \gamma^3 \frac{3}{4}\tau^2 \\ \$S-6681412-TP SCREW NS L=\frac{3}{2}\tau^2 \\ \$SH=0505800-SF SCREW NS L=\frac{8}{2}\tau^2 \\ \$SH=0505800-SF SCREW NS L=\frac{8}{2}	hxty* 9/32-28 L=13.5 E733* M5 L=8 77 7h* xyzah xyyy xyx* 7zah zyy 0.0	260 - 22400 SEA 5141 BUSHING, RIGHT SS-8681412-TP SCREW 9/32 - 28 L=13.5 SS-8681412-TP SCREW 9/32 - 28 L=13.5 SS-868142-TP SCREW 9/32 - 28 L=13.5 SS-8681412-TP SCREW 9/32 - 28 L=13.5 SS-8681412-TP SCREW 9/32 - 28 L=13.5 SS-8681412-TP SS-8681411111 SS-86814111 SS-86814111 SS-86814111 SS-86814111 SS-86814111 SS-8681411 SS-8681411				7A* - 9	
SS-8681412-TP SCREW 9/32-28 L=13.5 トメネケ・9/32- SW-6050800-SP SCREW W5 L=8 できます。M5 L=	とラネジ M5 L=8 ファ・ラト・メフェルト オクリタ・ソネジ・フェルト ユラン 0.0	SS-8681412-TP SCREW 9/32-28 L=13.5				カムケ・ケメタル(ミキ・)	
SN-6050800-SP SCREW M5 L=8 5743, M2 L=	77" ラト" メフェルト オクリタ" ソネシ" フェルト ユラン 0.0	SH-050800-SF SCREW NS L=8 E745" MS L=8				トメネク・9/32-28 L=13.5	
	オクリタ・ソネシ・フェルト ユラン 0.0	400-41045 OIL RETAINING FELT 77-75-75		SN-6050800-SP		とラネシ' M5 L=8	
0 400-41045 OIL RETAINING FELT 77° 51° ×71M	177 0.0	3 400-41044 FEED SNOULDER_SCREW_FELT #795" 724\ 4 CQ-2520000-00 01L WICK 25\ 5 CQ-3000000-F0 01L FELT 07\ 7 CQ-2520000-00 01L WICK 25\ 7 CQ-2520000-00 01L WICK 25\ 12\ 12\ 12\ 12\ 12\ 12\ 12\ 12\ 12\ 12				77" 51" ×7211	
400-41044 FEED SHOULDER SCREW FELT #795' 73		4 CQ-2520000-00 OIL WICK 25分 5 CQ-3000000-F0 OIL FELT 切り・フェルト 5 EA-9500801-00 CABLE BAND グラセン・ソト・ 7 CQ-2520000-00 OIL WICK 25分				オクリタ・ソネシ・フェルト	
CO-2520000-00 OIL WICK 1377	nwh. 2114 0.0	5 CQ-3000000-F0 OIL FELT BY 7.14 5 5 EA-9501001-10 CARLE BAND 79-5/7 CQ-252000-00 OIL WICK 137				ילנ	
5 CQ-300000-F0 OIL FELT U7h' 71h		6 EA-9500801-00 CABLE BAND 99€N 15.7 CQ-2520000-00 OIL WICK 1397			OIL FELT		
6 EA-9500B01-00 CABLE BAND 9747A' 71'		7 CQ-2520000-00 OIL WICK 1377			CABLE BAND		
ND 1977 III		NOTE (注記) #01FOR MB-1377 MB-1377用					

#01...FOR MB-1377 #02...FOR MB-1373 #03...SELECTIVE PARTS

MB-1373用 MB-1373用 選択軟息

6. BUTTON CLAMP LIFTER COMPONENTS

引き上げ関係




1		400-38119	LIFTING_LEVER	ヒキアケ・レハ・-
		260-18101	BUSHING	ハリオ・ウヨウト・ウカンシテング・クメタル
		400-38116	NEEDLE_BAR_LEVER	ハリオ・ウヨウト・ウカンシテンラ・ク
		WP-0851216-SC	WASHER 8.5X18.0X1.2	ቲ ን ታ *
		B4420-373-000	CUSHION	ラヤタ・ソ クラウヨン
	#01	WP-0851216-SC	WASHER 8.5X18.0X1.2	₹55° 7° 7 8.5X18X1.2
1	#01	WP-0751576-SD	WASHER 7.5X19X1.5	₹59° 7° 7° 7° 2811° 28
3	#01	105-10808	WASHER	クラッチへ・アリンク・カ・イリンワブシャ
•		WP-0751576-SD	WASHER 7.5X19X1.5	۲.5X19X1.5
		WP-0751576-SD	WASHER 7.5X19X1.5	セラチカネ 7.5X19X1.5
		B4420-373-000	CUSHION THE TYPE TYPE TYPE TYPE TYPE TYPE TYPE TYP	サナダ・ソ ケサラヨン ヒラサ・カ・ネ 7X20X3.5
2		WP-0703516-SP 260-33407	WASHER 7X20X3.5 SPRING	ドキュン・トン・- F ユン・カン・オ
3		260-33308	WASHER	ドキンチ・トレ・ートンレ・カレ・ナチ・カ・ナ
5		B4411-372-000	BUTTON CLAMP LIFTING LINK	£\$75. 18 x514. 1771
6		400-40962	ASSY SLIDING ROLLER	ヒキアケ・スライト・アンナイクミ
7		400-40953	SLIDING_ROLLER	ヒキアケ・イタスライト・アンナイ
8		SM-8060612-TP	SCREW M6 L=6	トメネク N6 L=6
9		400-38321	ECCENTRIC_CAM	ヒキアケ・ヘンクンカムクミ
0		400-38398	ECCENTRIC_CAM	ヒキアケ・ヘンランカム
1	1	SM-8060412-TP	SCREW	トメネツ M6 L=4
2		400-38146	BUTTON_CLAMP_LIFTING_LINK_SET	ヒキアケ・フタマタロット・_クミ ヒキアケ・フタマタロット・
3		400-40966 400-38149	BUTTON_CLAMP_LIFTING_LINK LIFTING_HOOK	E+77 /949471
5		SD-0640276-TP	SHOULDER SCREW D=6.35 H=2.7	タンネタ D=6.35 H=2.7
6		400-40963	TENSION SPRING RACK_B	ίλν. λ ν. τρλ Β
7		SD-0500726-TP	SHOULDER SCREW D=5 H=7.2	タ・ソネケ D=5 H=7.2
8	4	400-38150	LIFTING_HOOK_SPRING	ヒキアケ・ファクハ・ネ
9		NM-6050001-SP	NUT N5	ロプカクナプト N5X0.8 1シュ
0	1	WP-0410846-SC	WASHER	とラ サ ・カ・ネ
1		SM-6030402-TP	SCREW N3X0.5 L=4	ログカクアナ本・ルト
2		SD-0640481-SP	HINGE SCREW D= 6.35 H= 4.8	タ・ソネク・ D=6.35 H=4.8
3		SD-0640211-SP	HINGE SCRFW D= 6.35 H= 2.1	タンメン・D=6.35 H=2.1
4		WP-0330501-SB	WASHER M3	ヒラザ・カ・ネ ミカ・キマル M3
5		400-38283	L_TYPE_LIFTING_BAR_ROLLER BUTTON CLAMP_LIFTING_ROD_A	IND. 8641.0. *. DV
6		400-38502 SM-6061002-TP	SCREW M6 L=10	ロプカクフナオ・ルト NG L=10
17		400-38428	CONNECTING_LINK_FRONT	イトキリレンケブイタマエ
9		260-22202	JOINT STUD	イトキリレンクアン・ヨイント
0		B1632-180-000	FEED ADJUSTING JOINT	オクリチョーセブ ツ ヨイント
1		WP-0510516-SD	WASHER 5, 1X7, 5X0, 5	₹5, 7, 7, 2, 1X7, 5X0, 5
2		NM-6050001-SP	NUT M5	ロブカクナプト N5X0.8 1プユ
3		400-38219	CONNECTING_SCREW	イトキリレンケプネグ・
4		NM-6080021-SP	NUT M8 TYPEI	コカ・タロッカクナット M8 192
15		400-38429	CONNECTING_LINK_REAR	イトキリレンケブイタウラロ
6		SD-0640323-TP	HINGE SCREW D= 6.35 H= 3.2	タンネシ D=6.35 H=3.2
7		SD-0790402-TP	HINGE SCREW D= 7.94 H= 4	タ・ソネク・ D=7.94 H=4
8		NS-6620310-SP	NUT 3/16-32	ロプカクナプト 3/16-32 ロプカクナプト 15/64-28
9		NS-6150310-SP	NUT 15/64-28 THREAD TRIMMING LEVER	1579777 15764-26 イトキリレハ* -
0		400-38397 SD-0790316-TP	SHOULDER SCREW D=7.94 H=3.1	タングン D=7.94 H=3.1
2		NM-6050001-SP	NUT M5	ロブカクナット M5X0.8 17ユ
3		400-38495	THREAD TRIM_LEVER_BASE	イトキリレハ・ータ・イ
4		SN-7051460-TP	SCREW M5 L=14	マルとラコネク・ N5 L=14
5		260-21709	THREAD TRIMMING LINK	イトキリリンク
6		SD-0641322-TP	HINGE SCREW D=6.35 H=13.2	タ"ンネツ" D=6.35 H=13.2 ,
7	Talking.	260-33605	SPRING	フャタ・ソクァラヨンハ・ネ
8 .	() / () () () () () () () () (CS-0950810-SH	THRUST COLLAR ASM. D=9.5 W=8	スラストウケ D=9.5 W=8 クミ
59		CS-0950816-SH	THRUST COLLAR D=9.5 W=8	スラストウケ D=9.5 W=8
0		SS-8110410-TP	SCREW 11/64-40 L= 3.5	トメネツ 11/64-40 L=3.5
1		400-38445	LEVER_SHAFT	νν 3. 4
52		SM-8061010-TP	SCREW	トメネケ M6 L=10
53		260-32508 400-38414	LIFTING LINK	ヒキアケ・イタリンク ヒキアケ・イタアンナイロット・クミ
65		400-38414	LIFTING_PLATE_GUIDE_ROD_ASM LIFTING_PLATE_GUIDE_ROD	t+77 19777107h

NOTE (注記)

#01....SELECTIVE PARTS(USE OF ONE PARTS) 選択部品(いづれかー個使用)

7. NEEDLE DRIVING PULLEY SHAFT COMPONENTS


駆動軸関係



		DESCRIPTION	<u>Ł</u> . y x 1	Qt
I	B1203-372-000	BALL LARGE	‡h' - #' -#	
2	260-12401	PULLEY INSERT	\$1. 3\$8342. 1	
3	400-38203	BALL SWALL		
4	260-12500	SPRING	シュラ・クト・ネネ・ート	
5	400-38169	DRIVING_PULLEY ASM.	クト・ウァ・ーリクミ	
6	400-38175	DRIVING PULLEY	21. 2711	
7	SM-8040612-TP	SCREW M4 L=6	トメネシ ¥4 L=6	(
8	400-38449	NEEDLE_DRIVING_PULLEY_SHAFT	71. 44 T=0	(
9	B1243-372-000	NEEDLE BEARING		
0	260-12609	GREASE RTETAINING WICK	=- h. wv. 1377.	
1	260-12708	RETAINING WASHER	ウュラ・クアフ・ラト・メフェルトケース	
2	SM-6062450-TP	SCREW M6 L=23.5	シュシ・クフフ・ラト・メフェルトケース	
3	WP-0621026-SP	WASHER 6,2X9,5X1	とラコネケ M6 L=23.5	
4	B1208-372-000	NEEDLE DRIVING PULLEY CLUTCH D	₹57° 7° 2 6.2X9.5X1	
5	400-38137	STOP MOTION DISC ASM.	クト・- クサション	
6	400-38135	STOP_MOTION_DISC_LATCH A	シャダンカム_クミ	
7	400-38136	STOP_NOTION_DISC_LATCH B	シャタ・ソプメ_A	(
8	400-38138	STOP_MOTION_DISC_LAICH_B	シャタ・ソプメ_B	(
9	400-38139	STOP_MOTION_PAWL_SHAFT	シャタ・ソカム	(
0	400-38140	STOP_MOTION_DISC WASHER	シャタ・ソヨウナメケ・ク	(
	SM-6060550-TP	SCREW M6 L=4.5	シャダ・ソカムサ・カ・ネ	(
2	CM-5002000-01		とラコネツ M6 L=4.5	-
3	SM-8080812-TP	DIRECTION LABEL. SCREW M8X8	カイテンネウコウラへ・ル	
	SM-8081752-TP	SCREW M8 L=17	トメネシ. M8 T=8	
	NM-6060003-SP	NUT M6 TYPE3	トメネツ M8 L=17	
	B1215-372-B00	THRUST BALL BEARING	ロッカクナット M6 3シュ	
	SM-8061010-TP	SCREW	クト・・ケ・ク スラスト ヘ・ブリンク・	1
	400-38461		トメネシ M6 L=10	1
	400-42148	PULLEY_SHAFT_BUSHING_RIGHT	クト・ウケ・クメタルミキ・	1
	B1217-372-0BA	PULLET_SHAFT_BUSHING_LEFT	クト・ウシ・クメタルヒタ・リ	1
	SS-8660612-TP	DRIVING GEAR (A) ASM. SCREW 1/4-40 L=6	ネラ・ハケ・ルマA(クミ)	i
	260-18309	OIL WICK	トメネツ 1/4-40 L=6	(2
	200 13303	OIL WICK	クランクロット・ユウン	1

8. NEEDLE BAR DRIVING MECHANISM COMPONENTS


針棒関係



REF. NO	NOTE	PART NO.	DESCRIPTION		Qty
1		SS-7080510-TP	SCREW 1/8-44 L=4.5	マルヒラネン 1/8-44 L=4.5	1
2		146-06107	NEEDLE ROD	Vit. 4	1
3		260-17707	NEEDLE BAR BUSHING LOWER	ハリ本・ウシタメタル	1
4		400-40951	NEEDLE BAR BALANCE	カリオ・ウテンヒ・ン	1
5		400-40952	NEEDLE_BAR_CLAMP	via. 42. +	1
6	100	SM-6041200-SP	SCREW M4 L=12	ヒラネツ M4 L=12	1
7		400-38142	NEEDLE BAR BUSHING UPPER	ハリオ・ウウエメタル	1
8	#01	400-38120	NEEDLE BAR SLIDE BLOCK A	NJ本. ウタ. キンシイト. コム V	1
9	#01	400-38121	NEEDLE BAR SLIDE BLOCK B	NA本. みる. キンシイト. コム B	1
10	#01	400-38122	NEEDLE BAR SLIDE BLOCK C	Nリオ・ウタ・キスライト・コマ_C	1
11		MTQ-100B1600	NEEDLE TQX1 #16	Ny TQX1 #16	1
12		400-38117	NEEDLE_BAR_DRIVING_LEVER	עלם , ללבל , אוע	1
13 .		SM-9061403-CP	SCREW M6 L=14	ロッカクネ・ルト	2
14		SD-0950804-TP	SHOULDER SCREW D=9.53 H=8	タ・ソネケ D=9.53 H=8	1
15		260-18705	WASHER	クランクロット・サ・カ・ネ	1
16		260-18457	CRANK ROD ASM.	クランクロット・(クミ)	1
17		SS-2110920-TP	SCREW 11/64-40 L=8.5	マルチラネラ 11/64-40 L=8.5	(2)
18		260-18606	THRUST HOLDER	ハリオ・ウヘンシンカムスラストウケ	(1)
19		260-18408	CRANK ROD	クランクロット・	(1)
20		260-18507	ECCENTRIC CAM	ハリオ・ウヘンシンカム	(1)
21		SS-8660612-TP	SCREW 1/4-40 L=6	トメネシ 1/4-40 L=6	(1)
22		SS-8660942-TP	SCREW 1/4-40 L= 8.5	トメネジ 1/4-40 L=8.5	(1)
23		260-18309	OIL WICK	クランクロット・ユシン	1
24		400-41045	OIL RETAINING FELT	77. 24. 7224	1
25		CQ-2500000-F0	OIL WICK	וליי	0.01
26		CQ-2020000-00	OIL WICK	וליי	0.1
		NOTE (注記)	#01SELECTIVE PARTS	選択部品	

9. STOP MOTION MECAHNISM COMPONENTS


遮断装置関係



F. NO 1	NOTE PART NO.	DESCRIPTION		Qty
1	260-27805	STOP MOTION PLUNGER ROD	シャタ・ソヨウアッシュクシ・ク	
2	NM-6060003-SP	NUT M6 TYPE3	ロッカクナット N6 3シュ	
3	400-38118	CROSSING HOOK	ラャタ ・ソヨウファク	
4	SM-6061150-TP	SCREW M6 L=11	ヒラコネク M6 L=11	
5	B2602-372-000-A	STOP NOTION PLUNGER LEVER	シャタ・ ンフレーム	
6	262-29104	WASHER	シャタ・ハヨウハ・ネチ・カ・ネ	
7.	400-38110	STOP MOTION SPRING	シャタ· ソハ· ネ	3
8	B2608-280-000	RUBBER CUSHION	クト・- コ・ムクプラヨン	
9	260-30601	WASHER	グナダ・ソヨウコ、ムクテクヨンサ、カ、ネ	
0	NS-6680410-SP	NUT 9/32-28	ロプカクナプト 9/32-28	
1	400-38448	STOP_MOTION_SHAFT	ን ት ダ .	200
2	400-42437	SCREW	ラャタ・ソソウチトリッケネシ・	
3	SS-8151570-SP	SCREW 15/64-28 L=15.0	トメネケ 15/64-28 L=15	
4	NS-6150310-SP	NUT 15/64-28	ロプカクナット 15/64-28	
5	SD-0680276-TP	SHOULDER SCREW D=6.8 H=2.7	タンネグ D=6.8 H=2.7	
6	NM-6060001-CP	NUT M6	מא אפלעלעם M6	
7	SD-0710706-TP	SHOULDER SCREW D=7.14 H=7	タ・ンネタ・ D=7.14 H=7	
8	260-29207	STITCH ADJUSTING ROLLER	ヘリカス・チョウセプコロ	
9	WP-0612066-SP	WASHER 6.1X11X2	<u></u>	
0	260-19604	WASHER	イトチョウセグレハ・ータ・ソネグ・サ・カ・ネ	
1	SM-9061003-CP	SCREW M6 L=10	ロッカクネ・ルト	
2	400-38160	STOP_MOTION_TRIP_LEVER	キト・ウリンク	
3	260-28308	STOP MOTION TRIP LEVER BRACKET	キト・ウリンクトリックタ・イ	
4	SM-9061250-TP	SCREW M6 L=12	በታክባቱ እኑ M6 L=12	
5	229-24906	OIL REGULATOR SCREW SPRING	ユリヨウチョウセブネラ・ハ・ネ	
6	131-60304	S SHAPED HOOK	Sh. Apto.	
7	260-28001	STOP NOTION LEVER SPRING PIN	シャタ、ノソウチヒッハ・リル、ネトメト、フ	1
.8	400-38410	STOP_NOTION_LEVER_SPRING	シャタ・ソフレーヤドブル・リル・オ	
9	400-40940	SCREW STUD	ネシ゚スタ゚ット ゙	
30	B2611-373-N00	PRESSURE APPLYING LEVER	クト・ウフ・ーリ オラッケイタ	

10. STITCH SELECTING PARTS COMPONENTS


針数調節関係



REF. NO	NOTE PART NO.	DESCRIPTION	t.y*t	Qt
1	SD-1270346-TP	SHOULDER SCREW D=12,7 H=3,4	5" >>> D=12.7 H=3.4	
2	260-30304	SPRING FOR FRICTION PLATE	79719670 10. 1	
3	260-30007	FRICTION PLATE ROTATING SHAFT	797 (99 (7)) 7	
4	WP-0850002-SP	WASHER 8,5X18X1.6	k5+ 4 1 8 5X18X1 6	
5	260-30908	SPEED SLOWING LEVER		1
6	260-31005	FITTING PLATE	3k. シイントレ	
7	260-30106	FRICTION PLATE HOLDER	36, 24204, -122242	100
8	B2640-372-000	SPEED SLOWING FRICTION PLATE	7971919779 1	1
9	B3211-232-000	POSITIONING PIN	3と・テーク マチフィダ	1
10	NS-6110310-SP	NUT 11/64-40	クオーム キューコイタ カラメヒ・ソ	2
T -	SD-0710706-TP	SHOULDER SCREW D=7 14 H=7	ロブカクナプト 11/64-40	1
2	B2629-372-000		3"745" D=7.14 H=7	
3	400-40943	STITCH SELECTING SPUR GEAR, MI	N## ₹3-+7 N7 47 (₹1-)	1
4	400-40942	INTERNEDIATE GEAR SHAFT	チュウカントク・ルマナ・ク	1
5	SM-8061010-TP	ASSY_SPEED_SLOWING_FRICTION_WH	3と、テイクマチブク、ルマクミ	1
6	400-40944	SCREW	トメネク M6 L=10	(2
7		SPEED_SLOWING_FRICTION_WHEEL	36, 242443, 74	(1
8	B2630-372-000-A	GEAR, LARGE	ハリカズ チョウセフョウハケ ルマ(ダ イ)	,
9	B2631-372-000	SCREW	VAPS. 43-42 VV. 84 4475.	i
0	B2632-372-000-A	ROLLER	ハリカス・チョウセブハク・4マ(ダ・イ)コロ	1
1	400-40946	THREAD_BIND_NOTCH	11475. 174	
1	260-30809	SPACER	11476, 14424, -4	-
2	SN-6040560-TP	SCREW M4X0.5 L=4.5	t7327 W4X0.5 L=4.5	
	SM-6050800-SP	SCREW N5 L=8.	t717 M5 L=8	2
4	SD-0800341-SP	HINGE SCREW D=8 H=3 4	3" >3" D=8 H=3.4	
5	400-38269	STITCH ADJUSTING ARM ASM.	ハリカス・チョウセブウテ・クミ	
5	400-38271	STITCH ADJUSTING ARM	NJDX 730+707'	
7	SN-6061602-TN	SCREW M6 L=16	u7b777* % M6 L=16	()
8	260-29207	STITCH ADJUSTING ROLLER	ハリカズ・チョウセブコロ -	(1
9	409-41046	STITCH_ADJUSTING_CAM A ASSY		
0	400-41054	STITCH ADJUSTING CAM A ASM.	ハリカス チョウセアカムムクミ	1
	400-41050	NUT	ハリカス・チョウセブカムハクブコ・ウ	(1
2	400-38304	SCREW	171	()
3	SN-6040502-TP	SCREW M4X0.7 L=5	ハリカス・ チョーセブイタトメネク・	(1
1	SM-6040800-SP	SCREW	ロブカクアナオ ルト N4 L=5	(1
5	SM-8060812-TP	SCREW N6 L=8	とラネク・	(2
5	400-41048	SPACER NO L=8	► トメネク W6 L=8	(2
,	400-41049		2A'-9-	(1
8	400-41049	STITCH_CAN_A	ZTTFDAA	(1
	400-41051	STOP NOTION CAM SHOE	ストラフ・モークョンカムウュウ	(1

11. THREAD BIND NOTCH COMPONENTS (FOR MB-1377)


糸結び関係 (MB-1377用)



REF. NO N	NOTE PART NO.	DESCRIPTION	t.y±.1	- Qty
1 2 3	400-38488 400-38452 SD-0640328-TP 400-38486	THREAD_BIND_LEVER CONNECTING_PLATE_LARGE SHOULDER SCREW D=6.35 H=3.2 CONNECTING_PLATE_SMALL	イトムスセ・レハ・- イトムスセ・レンケブイタタ・イ タ・ソネシ・ D=6.35 H=3.2 イトムスセ・レンケブイタショウ	1 1 1 1
5 6 7 8	WP-0430800-SD SM-6040650-TP SD-0720336-SP D2509-282-A00	WASHER M4 SCREW SHOULDER SCREW WORK CAMP FOOT BALL LINK THREAD BIND LINK SHAFT	ヒラザ・カ・ネ コカ・ダマル M4 ヒラネシ・ M4 L=6 ダ・ンネン・ サマミアラ オ・ - ルリンク イトムスピ・リンクシ・ク	2 1 1 2
9 10 11 12	400-38489 WP-0621026-SP RC-0560711-KP NM-6050001-SP	WASHER 6.2X9.5X1 RETAINING RING NUT M5	ቲንፃ	2 1
13 14 15	400-38456 NM-6050001-SP 400-38494 260-17103	THREAD_BIND_ARM_B NUT M5 THREAD_BIND_ARM_SPRING RAC SPRING	イトムスセ・ウテ・Bケブコ・ウ ロサカケナナト M5X0.8 1シュ イトムスセ・ウテ・ハ・ネカケ イトムスセ・ウテ・ハ・ネ	1 1
16 17 18 19	SD-0901806-TP 260-17301 SD-0460576-TP NM-6040001-SP	SHOULDER SCREW ROLLER SHOULDER SCREW D=4.6 H=5.7 NUT M4X0.7	タンステン・D=9 H=18 イトムスと・コロ タンステン・D=4.6 H=5.7 ロサカクナフト M4X0.7 1シュ	1 1 1 1
20 21 22 23 24	SD-0481456-TP 400-38306 400-38305 400-38455	SHOULDER SCREW D=4.8 H=14.5 SPRING STITCH_ADJUSTING_CAM_KNOB ASS_THREAD_BIND_ARM_A	タ・ンネジ・ D=4.8 H=14.5 ハリカズ・チョーセブ ブマミハ・ネ ハリカズ・チョーセブ ブマミ イトムスと・ケデ・Aケブコ・ウ	1 1 1 1

12. THREAD STAND COMPONENTS


糸立装置関係



REF. NO	NOTE PART NO.	DESCRIPTION		Qty
1	260-08359	THREAD STAND ASM.		
2	229-30408	SPOOL REST ROD, UPPER	イトタテソウチ(クミ)	1
3	229-30309	SPOOL REST ROD, LOWER	イトタテオ・ウ(ウェ)	(1)
4	260-08300	THREAD STAND HOLDER PLATE	イトタテオ・ウ(シタ)	(1)
5	260-08409	THREAD RAISING THREAD GUIDE A	イトタテウケイタ	(1)
6	229-31307	SPOOL REST ROD JOINT	イトタテイトアンナイ(A)	(1)
7	229-31406	SPOOL REST ROD RUBBER CAP	イトタテオ・ウツキ・テ	(1)
8	229-31000	SPOOL PIN	√トタテオ、ウオコ、コ、↑	(1)
9	229-30903	SPOOL REST CUSHION	イトマキウケオ・ウ	(1)
10	229-31109	SPOOL RETAINER	イトマキウケチ・ラクッション	(1)
11	WP-1612616-SE	WASHER 16X30X2.6	イトマキフレト・メ	(1)
12	NM-6160511-SE	NUT M16X1.5	ヒラザ・カ・ネ	(2)
13	260-08557	SPOOL REST BRACKET ASM	ロブカクナプト M16X1.5 1シュ	(3)
14	- SM-4051405-SE	SCREW M5 L=14	イトタテウケタ・イ(イツオ・ソヨウ)クミ	(1)
15	NM-6050001-SE	NUT M5	ナペコネシ゚ M5 L=14	(2)
16	NM-6050001-SE	NUT M5	ロプカクナット M5	(2)
17	SM-9061080-SE	SCREW M6 L=10	ロッカクナット M5	(1)
18	SM-9050813-SE	SCREW M5X0.8 L=8	ロブカク木・ルト M6 L=10	(1)
19	WP-0520656-SA	WASHER 5.2X9.5X0.6	ロブカク本 ルト M5XO.8 L=8	(1)
20	WS-0510002-KN	SPRING WASHER	ヒラチ カ ネ 5.2X9.5X0.6	(1)
21	WS-0521010-KN	SPRING WASHER 5.2X8.2X1	ハ・ネサ・カ・ネ 5.1X9.2X1.3	(1)
22	229-31208	THREAD GUIDE	ハ·ネラ·カ·ネ 5.2X8.2X1	(1)
	220 01200	IIIILAD GOIDE	仆封	(1)

is all he name.


13. TABLE & STAND COMPONENTS 脚阜関係



REF. NO	NOTE PART NO.	DESCRIPTION		Qty
1 2 3 4 5	400-40971 111-59365 111-55108 111-55207 D8204-555-D00	TABLE T STAND JUNCTION DRAWER DRAWER SUPPORT DRAWER STOPPER	テーア・ル Tキャクケタコ・ウ ヒキタ・ラ ヒキタ・ラ サテエ	1 1 1 2
6 7	SK-3311600-SE SK-3483200-SE	WOOD SCREW D=3.1 L=16 WOOD SCREW D=4.8 L=32	セキタ・ラストラハ・- モクネラ・ D=3.1 L=16 マルモクネラ・ D=4.8 L=32	6 4

14. ACCESSORIE PARTS COMPONENTS


付属品関係



REF. NO	NOTE PART NO.	DESCRIPTION		Qty .
	229-33103	VINYL COVER	ト ウ ፖ' ヒ' =- <i>እስ</i> ∧' -	1
1	229-33006	SCREW DRIVER, LARGE	ト・ライハ・- (ダ・イ)	1
2	MTQ-100B1602	NEEDLE TQX1 #16-2	TQX1#16-2	1
3	400-41072	BASE SCREW SET	A. カト・トリタケタ・イネン・セット	1
5	400-38174	RUBBER CUSHION	*. 42,73. Y	(4)
	SS-9156830-SP	SCREW 15/64-28 L=68	ロブカクネ Aト 15/64-28 L=68	(4)
6	WP-0612056-SD	WASHER 6.1X18.5X2	とラチ・カ・ネ 6.1X18.5X2	(4)
,	NS-6150310-SP	NUT 15/64-28	ロッカクナット 15/64-28	(4)
8	400-41073	ACCESSORIE BAG ASM.	フソ・クヒンハ・ック・クミ	1
9	229-33105	SCREW DRIVER, MIDDLE	ト・ライル・- (チュウ)	(1)
10	260-34702	WRENCH	リョウク・チスハ・ナ(ダ・イ) 14X11	(1)
11	260-34801	WRENCH	リョウケ・チスト・ナ(ブョウ) 7X8	(1)
12	400-33327	FRAME SUPPORT_BAR	トウア・サラエカ・ウ	(1)
13		STITCH NUMBER_LEVER	ハリカス・チョウセグレハ・-	(1)
14	400-38459		イトムスと、ノッチスヘ・ーラ	(1)
15	260-30809	SPACER NOTCH	11426. 144	(1)
16	400-40946	THREAD_BIND_NOTCH	とラコネラ M4X0.5 L=4.5	(2)
17	SM-6040560-TP	SCREW M4X0.5 L=4.5	Sp. 3977.	(2)
18	131-60304	S SHAPED HOOK	タンスタ D=6 H=3.4	(1)
19	SD-0600346-TP	SHOULDER SCREW D=6 H=3.4	いま、ウカハ・-	(1)
20	400-38205	NEEDLE_BAR_GUARD	799	(1
21	260-37903	CHAIN	77' 75'	(1
22	J1067-000-000	OILER	77. 4F7V. 24.	(1
23	229-32800	ACCESSORIE BAG		(1
24	400-55591	HEXAGONAL WRENCH KYE	ロッカクネ・ウスハ・ナ3 Vローフ・ 900MM(レーランク・ブキ)	- (1
25	MTJ-VN00000C	V ROPE 820MM (LACING)		
26	400-38286	MOTOR_PULLEY_60HZ_1300RPM_ASM.	₹-ダ-7°-У60HZ_1300RPMク	(2
27	SM-8061010-TP	SCREW	トメネケ M6 L=10	
28	400-38285	MOTOR_PULLEY_50HZ_1300RPM_ASM.	t-4-7 -y50HZ_1300RPM1	(2
29	SM-8061010-TP	SCREW	トメネን M6 L=10	(2

15. SPECIAL ORDER SPEC COMPONENTS


特別仕様関係



REF. NO	NOTE PART NO.	DESCRIPTION	t y x 1	Qty
1	MAZ-201010A0	PICK-UP DEVICE ASM. L BUTTON	\$. 4\$. \$\text{\$\frac{1}{2}} \dots \d	1
2	400-38290	MOTOR_PULLEY_50HZ_1500RPM_ASM	t-9-7'-950HZ_1500RPM7	i
3	B2556-372-0AA	BUTTON CLAMP JAW LEVER ASM., L	クヨーオ・タンヨー クマミアグ ヒダ・リ クミ	1
4	B2558-372-0AA	BUTTON CLAMP JAW LEVER ASM., R	クヨーオ・タンヨー クマミアウ ミキ・クミ	1
5	D2556-372-CAA	BUTTON CLAMP JAW LEVER ASM., L	タ・イオ・タンヨー サマミアラ ヒダ・リ クミ	1
6	D2558-372-CAA	BUTTON CLAMP JAW LEVER ASM: R	ダ イオ・ダンヨー グマミアク ミキ・ クミ	1
7	D2529-373-C00-	A FEED PLATE, LARGE BUTTON	ヌノオサエツタイタ(ダ・イ本・タン)	1

16. SUBCLASS COMPONENTS (FOR MB-1373-11)

サブクラス関係 (MB-1373-11用)



REF.	O NOTE	PART NO.	 D	E S	C R	1.	P.T.	1_0	N	 	 	!	-	٧	. ¥.	.1	 	 	Qty	
1		400-41032	LENGTHWA	ISE	FEE	CD I	CAM (X)			+	• '	· *	クリカ	A(X)			1	